## **TP562-T**

**TP Series Touch Screen** 

5.7 inch, 256 color TFT, 320\*240 pixels 4MB FlashROM, 4KB SRAM

With data display , data monitor, alarm, scheme and relevant functions Support various popular PLC, double separated communication ports

It's own screen edit software support simulate offline and simulate online as well as configuration function. It's own screen edit software support simulate offline and simulate online as well as configuration function.

## Specifications

configuration fu		IA ANA
·	Harry of Marketon	
Electrical Features	Input Voltage	DC22-DC26V
		<180mA
	Allowable Momentary Power-cut	Less than 20ms
	Voltage Endurance	AC1000V-10mA for 1 minute (between signal and time)
	Insulated Resistance	DC500V-about 10M $\Omega$ (between signal and time)
Interfaces	Communication Port	RS-232/RS-422/RS-485
	Download Port	RS-232
Environment	<b>Operation Temperature</b>	0-50°C
	Storage Temperature	-20-60°C
	Ambient Humidity	20-85% (non-condensing, try bulb)
	Vibration Resistance	10-25HZ (X, Y, Z directions for 30 minutes 2G)
	Interference Rejection	Noise voltage: 1000Vp-p, Pulse cycle:1us, Duration: 1minute
	Atmosphere	Free of corrosive gas
	Protect Configuration	IP65
Screen properties	Туре	256 color TFT
	Screen Size	5.7 inch
	Lifetime	Above 50000 hours, Environmental temperature 25°C, 24 hours operating
	Display area	320*234
	Brightness	Can not be adjusted
	Languages	Chinese : Simplified/Traditional, English, Japanese, Korean, etc.
	Font & Size	Optional font, Optional size
	Touch Panel	Digital matrix
Memory	Screen	4MB
	Data	4KB
Structure	Cooling method	Natural air cooling
	External Dimensions	200.0*148.0*44.4(mm)
	Cutout Dimensions	182.4*134.4(mm)